

Pocket type



PM7a

Updated longtime seller

- 3-3 / 4 digits 4000 count
- 0.7% best accuracy
- Range hold
- Auto power off (15min.)
- Low power ohm (input voltage 0.4V) at continuity range
- Power saving design

Display : numeral display 4000

Sampling rate : 3 times / sec.

AC frequency bandwidth : 40~400Hz



Function	Measuring range	Best accuracy	Resolution	Input impedance
DCV	400m/4/40/400/500V	$\pm (0.7\%+3)$	0.1mV	DCV: 10M $\sim$ 100M Ω
ACV	4/40/400/500V	$\pm (2.3\%+10)$	0.001V	ACV: 10M $\sim$ 11M Ω
Resistance	400/4k/40k/400k/4M/40M Ω	$\pm (2.0\%+5)$	0.1 Ω	
Continuity	Buzzer sounds at less than 10 $\sim$ 120 Ω . Open voltage : 0.4V			
Diode test	Open voltage : approx. 1.5V			
Bandwidth	40~400Hz			
Battery	Button battery LR-44 $\times$ 2			
Size / Weight	H115 $\times$ W57 $\times$ D18mm/approx. 85g			
Standard accessories included	Instruction manual			

Optional accessories

Clip adapter : CL-11, TL-81C



PS8a

Solar charge battery DMM

- 3-3 / 4 digits 4000 count
- 0.7% best accuracy
- Range hold
- Auto power off (15min.)
- Low power ohm (input voltage 0.4V) at continuity range
- Power saving design

Display : numeral display 4000

Sampling rate : 3 times / sec.

AC frequency bandwidth : 40~400Hz



Function	Measuring range	Best accuracy	Resolution	Input impedance
DCV	400m/4/40/400/500V	$\pm (0.7\%+3)$	0.1mV	DCV: 10M $\sim$ 100M Ω
ACV	4/40/400/500V	$\pm (2.3\%+5)$	0.001V	ACV: 10M $\sim$ 11M Ω
Resistance	400/4k/40k/400k/4M/40M Ω	$\pm (2.0\%+5)$	0.1 Ω	
Continuity	Buzzer sounds at less than 10 $\sim$ 120 Ω . Open voltage : 0.4V			
Diode test	Open voltage : approx. 1.5V			
Bandwidth	40~400Hz			
Battery	Amorphous solar battery + manganese dioxide lithium secondary battery			
Size / Weight	H115 $\times$ W57 $\times$ D18mm/approx. 85g			
Standard accessories included	Instruction manual			

Optional accessories

Clip adapter : CL-11, TL-81C